



Flash unit information that I have gathered over the years.  
Please contact me with information of any units that I may have missed out.  
(I can not be held responsible for any changes in manufacturer's specs or errors in the information below)

---

## BOWENS STUDIO FLASH EQUIPMENT

| Model       | Power Output | Guide No (m) | Modelling bulb           | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec | Tube_Code                   |
|-------------|--------------|--------------|--------------------------|----------|-----------|-----------|-----------|-----|---------------|------------|-----------------------------|
| Esprit 125  | 125          | 41           | 240v 275W E.S photoflood | 5600     | F5A       | -         | 15v       | No  | Yes           |            | BW1074(UV) or BW1075(clear) |
| Esprit 250  | 250          | 60           | 240v 275W E.S photoflood | 5600     | F5A       | -         | 15v       | No  | Yes           |            | BW2032(UV) or BW2030(clear) |
| Esprit 500  | 500          | 82           | 240v 275W E.S photoflood | 5600     | F5A       | -         | 15v       | No  | Yes           |            | BW2032(UV) or BW2030(clear) |
| Esprit 1000 | 1000         | 120          | 240v 275W E.S photoflood | 5600     | F5A       | -         | 15v       | No  | Yes           |            | BW1079(UV) or BW2980(clear) |

|                    |      |     |                          |      |      |      |     |    |     |                                                   |                                        |
|--------------------|------|-----|--------------------------|------|------|------|-----|----|-----|---------------------------------------------------|----------------------------------------|
| Esprit 1500        | 1500 | 160 | 240v 650W Halogen        | 5600 | F10A | -    | 15v | No | Yes | Switchable to act as 500, 1000 or 1500 Watt light | BW2981(UV Cover Dome) or BW2980(clear) |
| Esprit II 125      | 125  | 41  | 240v 275W E.S photoflood | 5600 | F5A  | -    | 15v | No | Yes |                                                   | BW1074(UV) or BW1075(clear)            |
| Esprit II 250      | 250  | 60  | 240v 275W E.S photoflood | 5600 | F5A  | -    | 15v | No | Yes |                                                   | BW2032(UV) or BW2030(clear)            |
| Esprit II 500      | 500  | 82  | 240v 275W E.S photoflood | 5600 | F5A  | -    | 15v | No | Yes |                                                   | BW2032(UV) or BW2030(clear)            |
| Esprit II 1000     | 1000 | 120 | 240v 275W E.S photoflood | 5600 | F10A | -    | 15v | No | Yes |                                                   | BW1079(UV) or BW2980(clear)            |
| Esprit II 1500     | 1500 | 160 | 240v 650W Halogen        | 5600 | F10A | -    | 15v | No | Yes | Switchable to act as 500, 1000 or 1500 Watt light | BW2981(UV Cover Dome) or BW2980(clear) |
| Esprit 250DX       | 250  | 60  | 240v 275W E.S photoflood | 5300 | F5A  | -    | 14v | No | Yes | IR remote control                                 | BW2032(UV) or BW2030(clear)            |
| Esprit 500DX       | 500  | 82  | 240v 275W E.S photoflood | 5300 | F5A  | -    | 14v | No | Yes | IR remote control                                 | BW2032(UV) or BW2030(clear)            |
| Esprit 1000DX      | 1000 | 120 | 240v 275W E.S photoflood | 5300 | F5A  | -    | 14v | No | Yes | IR remote control                                 | BW1079(UV) or BW2980(clear)            |
| Esprit 750 PRO     | 750  | 102 | 240v 650W E.S halogen    | 5300 | T15A | -    | 14v | No | Yes | IR remote control                                 | BW2981(UV) or BW2980(clear)            |
| Esprit Digital 750 | 750  | 102 | 650W GX6.35 base         | 5300 | T15A | F4A  | 14v | No | Yes |                                                   | BW-2980 (UV-coated)                    |
| Esprit Gemini 125  | 125  | 41  | 240v 275W E.S photoflood | 5600 | F5A  | -    | 5v  | No | Yes | Designed for operation with travel-Pak            | BW1074(UV) or BW1075(clear)            |
| Esprit Gemini 200  | 200  | 50  | 240v 250W E.S photoflood | 5600 | F5A  | -    | 5v  | No | Yes | Designed for operation with travel-Pak            | BW2032(UV) or BW2030(clear)            |
| Esprit Gemini 250  | 250  | 60  | 240v 275W E.S photoflood | 5600 | F5A  | -    | 5v  | No | Yes | Designed for operation with travel-Pak            | BW2032(UV) or BW2030(clear)            |
| Esprit Gemini 500  | 500  | 80  | 240v 275W E.S photoflood | 5600 | F5A  | -    | 5v  | No | Yes | Designed for operation with travel-Pak            | BW2032(UV) or BW2030(clear)            |
| Esprit Gemini 750+ | 750  | 104 | 240v 275W E.S photoflood | 5600 | F5A  | -    | 5v  | No | Yes | Designed for operation with travel-Pak            | BW1079(UV) or BW2980(clear)            |
| MonoBronze         | 300  | 79  | 240v 275W E.S photoflood | 5600 | 5A   | 5A   | 15v | No | No  |                                                   | (not user-changeable)                  |
| MonoGold           | 1100 | 168 | 240v 650W (Thorn P2/16 ) | 5600 | 6.3A | 6.3A | 15v | No | No  |                                                   | (not user-changeable)                  |

| Model                | Power Output | Guide No (m) | Modelling bulb           | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec                                 | Tube_Code             |
|----------------------|--------------|--------------|--------------------------|----------|-----------|-----------|-----------|-----|---------------|--------------------------------------------|-----------------------|
| Monolite 200D        | 125          | 54           | 240v 150W E.S fitting    | 5600     | 5A        | 0.6A slow | 35v       | No  | No            | Full or Half power setting                 | (not user-changeable) |
| Monolite 200E        | 125          | 54           | 240v 150W E.S fitting    | 5600     | 5A        | 0.6A slow | 220v      | No  | No            | Full or Half power setting                 | (not user-changeable) |
| Monolite 400D        | 250          | 74           | 240v 275W E.S photoflood | 5600     | 5A        | -         | 35v       | No  | No            |                                            | (not user-changeable) |
| Monolite 400E        | 250          | 74           | 240v 275W E.S photoflood | 5600     | 5A        | -         | 220v      | No  | No            |                                            | (not user-changeable) |
| Monolite 750 special | 750          |              |                          | 5500     | 5A        | -         | 220v      | No  | No            |                                            | (not user-changeable) |
| Monolite 800         | 800          | 126          | 240v 275W E.S photoflood | 5500     | 5A        | -         | 35v       | No  | No            |                                            | (not user-changeable) |
| MonoSilver           | 500          | 101          | 240v 275W E.S photoflood | 5500     | 5A        | 5A        | 15v       | No  | No            |                                            | (not user-changeable) |
| MonoSpot             | 380          | -            | 12v 100W                 | 5500     | 5A        | -         | 35v       | Yes | No            |                                            | (not user-changeable) |
| Prolite 100          | 750          | 100          | 240v 250W E.S photoflood | 5300     | F5A       | -         | 15v       | No  | Yes           | Can be powered by battery pack (12 or 24v) | BW-1089               |
| Prolite 120          | 1000         | 120          | 240v 650W P2/16          | 5500     | 6.3A      |           | 15v       | No  | Yes           |                                            |                       |
| Prolite 41           | 150          | 41           | 240v 275W E.S photoflood | 5300     | F5A       | -         | 15v       | No  | Yes           |                                            | (not user-changeable) |
| Prolite 41A          | 150          | 41           | 240v 150W E.S photoflood | 5300     | F5A       | -         | 15v       | No  | No            |                                            | (not user-changeable) |
| Prolite 60           | 250          | 60           | 240v 275W E.S photoflood | 5300     | F5A       | -         | 15v       | No  | Yes           | Can be powered by battery pack (12 or 24v) | BW-1026               |
| Prolite 82           | 500          | 82           | 240v 275W E.S photoflood | 5300     | F5A       | -         | 15v       | No  | Yes           | Can be powered by battery pack (12 or 24v) | BW-1026               |
| Super Bo-Lite        | 170          | 41           | 100W E.S frosted         | 5500     | 3.15A     | -         | 30v       | No  | No            |                                            | (not user-changeable) |

---

# COURTENAY STUDIO FLASH EQUIPMENT

| Model           | Power Output | Guide No (m) | Modelling bulb         | Temp (K) | Main fuse | Lamp fuse | Synch (V)      | Fan | Built-in cell | Other_Spec                 | Tube_Code             |
|-----------------|--------------|--------------|------------------------|----------|-----------|-----------|----------------|-----|---------------|----------------------------|-----------------------|
| Colorflash 2    | 100          | 27           | 240v 150W ES type P3/4 | 5500     | -         | T0.63A    | 18v pos. earth | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 1000  | 100          | 27           | 240v 150W ES type P3/4 | 5600     | -         | T0.63A    | 18v pos. earth | No  | No            | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 1000s | 100          | 27           | 240v 150W ES type P3/4 | 5600     | -         | T0.63A    | 18v pos. earth | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 1150  | 115          | 27           | 240v 150W ES type P3/4 | 5600     | -         | T0.63A    | 18v pos. earth | No  | No            | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 1250  | 125          | 30           | 240v 150W ES type P3/4 | 5600     | -         | T0.63A    | 18v pos. earth | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 2000  |              | 30           | 240v 150W ES type P3/4 | 5600     | -         | T1.6A     |                | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 2500  | 250          | 42           | 240v 150W ES type P3/4 | 5600     | -         | T1A       | 18v pos. earth | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 4000  |              | 42           | 240v 275W ES type P3/4 | 5600     | -         | T1.6A     |                | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 4000s | 230          | 42           | 240v 150W ES type P3/4 | 5600     | -         | T1.6A     | 18v pos. earth | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 8000  |              | 60           | 240v 275W ES type P3/4 | 5600     | -         | T2A       |                | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |
| Solaflash 8000s | 460          | 60           | 240v 150W ES type P3/4 | 5600     | T2A       | T3.15A    | 18v pos. earth | No  | Yes           | Recommended plug fuse = 5A | (not user-changeable) |

---

# ELINCHROM STUDIO FLASH EQUIPMENT

| Model              | Power Output | Guide No (m) | Modelling bulb            | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec                                      | Tube_Code             |
|--------------------|--------------|--------------|---------------------------|----------|-----------|-----------|-----------|-----|---------------|-------------------------------------------------|-----------------------|
| D-Lite 2           | 12 - 200     | 45           | 240v<br>100W/E27          |          |           |           | 5v        | No  | Yes           | Works on 90 to 240 volt supply                  |                       |
| D-Lite 4           | 25 - 400     | 64           | 100W/E27                  |          |           |           | 5v        | No  | Yes           | Works on 90 to 240 volt supply                  |                       |
| EL 1000            | 1000         | 114          | 240v 200W                 | 5400     |           | -         |           | No  | Yes           |                                                 | 24034                 |
| EL 1500R           | 1500         | 132          | 240v 200W                 | 5500     |           | -         |           | No  | Yes           |                                                 | 24053                 |
| EL 250             | 250          | 54           | 240v 100W                 | 5400     |           | -         |           | No  | Yes           |                                                 | 24031                 |
| EL 250R            | 250          | 45           | 240v 100W                 | 5500     |           | -         |           | No  | Yes           | Flash duration only 1/6400 second at half power | 24064                 |
| EL 500             | 500          | 76           | 240v 100W                 | 5400     | T4A       | -         |           | No  | Yes           |                                                 | 24031                 |
| EL 500R            | 500          | 64           | 240v 100W                 | 5500     |           | -         |           | No  | Yes           | Flash duration only 1/4000 second at half power | 24064                 |
| EL Universal 1500S | 1500         | 136          | 240v 200W                 | 5400     |           |           |           | No  | Yes           |                                                 | 24034                 |
| EL Universal 750S  | 750          | 96           | 240v 200W                 | 5400     |           |           |           | No  | Yes           |                                                 | 24034                 |
| Micro 750 Compact  | 750          | 96           | 240volt 300W              | 5500     |           | -         |           | No  | Yes           | Dual voltage AC supply capability               | 24064                 |
| Style 100BX        | 6 - 100      | 32           | 100W/E27                  |          |           |           | 5v        | Yes | Yes           | Works on 90 - 240volts.                         | 24029                 |
| Style 100FX        | 6 -100       | 32           | 100W/E27                  |          |           |           | 5v        | Yes | Yes           | (tube not user-changeable)                      | 24032                 |
| Style 1200RX       | 37 - 1200    | 128          | 300W GX 6.35<br>230v      |          |           |           | 5v        | Yes | Yes(2)        |                                                 | 24029                 |
| Style 300          | 300          | 46           | 100W fitted<br>(250W max) |          | T5A       | F2.5      | 12v       | No  | Yes           | Amphenol (Elinchrom standard) or 3.5mm jack     | (not user-changeable) |
| Style 300 S        | 300          | 46           | 250W                      |          | T5A       | F2.5      | 12v       | No  | Yes           | Elinchrom or 3.5mm synch jack                   | 24029                 |
| Style 300RX        | 9 - 300      | 64           | 250W/E27                  |          |           |           | 5v        | Yes | Yes           |                                                 | 24029                 |
| Style 400BX        | 25 - 400     | 64           | 100W/E27                  |          |           |           | 5v        | Yes | Yes           | Works on 90 - 240 volts.                        | 24029                 |

|                |          |    |                           |       |      |     |     |     |                                                |                           |
|----------------|----------|----|---------------------------|-------|------|-----|-----|-----|------------------------------------------------|---------------------------|
| Style 400FX    | 25 - 400 | 64 | 100W/E27                  |       |      | 5v  | Yes | Yes | (tube not user-changeable)                     | 24032                     |
| Style 600      | 600      | 65 | 100W fitted<br>(250W max) | T6.3A | F2.5 | 12v | No  | Yes | Amphenol (Elinchrom<br>standard) or 3.5mm jack | (not user-<br>changeable) |
| Style 600 S    | 600      | 65 | 250W                      | T6.3A | F2.5 | 12v | No  | Yes | Elinchrom or 3.5mm synch<br>jack               | 24029                     |
| Style<br>600RX | 18 - 600 | 90 | 250W E27                  |       |      | 5v  | Yes | Yes |                                                | 24029                     |

## INTERFIT STUDIO FLASH EQUIPMENT

| Model        | Power Output | Guide No (m) | Modelling bulb | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec     | Tube_Code |
|--------------|--------------|--------------|----------------|----------|-----------|-----------|-----------|-----|---------------|----------------|-----------|
| EX150        | 18 - 150     | 30           | INT515-60W     | 5600     |           |           | 5v        | No  | Yes           | EX fitting     |           |
| EXD200       | 25 - 200     | 45           | INT515-60W     | 5600     |           |           | 5v        | Yes | Yes           | EX fitting     |           |
| Stellar 1000 | 32 - 1000    | 30           | INT500-250W    | 5600     |           |           | 5v        | Yes | Yes           | S type fitting |           |
| Stellar 150  | 4 - 150      | 38           | INT499-150W    | 5600     |           |           | 5v        | Yes | Yes           | S type fitting |           |
| Stellar 300  | 9 - 300      | 30           | INT499-150W    | 5600     |           |           | 5v        | Yes | Yes           | S type fitting |           |
| Stellar 600  | 75 - 600     | 30           | INT500-250W    | 5600     |           |           | 5v        | Yes | Yes           | S type fitting |           |
| Venus 150    | 18 - 150     | 39           | INT515-60W     | 5600     |           |           | 5v        | Yes | Yes           | S type fitting |           |
| Venus 300    | 37 - 300     | 55           | INT498-100W    | 5600     |           |           | 5v        | Yes | Yes           | S type fitting |           |

## MULTIBLITZ STUDIO FLASH EQUIPMENT

| Model          | Power Output | Guide No (m) | Modelling bulb            | Temp (K) | Main fuse | Lamp fuse  | Synch (V) | Fan | Built-in cell | Other_Spec             | Tube_Code             |
|----------------|--------------|--------------|---------------------------|----------|-----------|------------|-----------|-----|---------------|------------------------|-----------------------|
| Compactlite    | 100 - 200    | 47           | 230v 60W FILHAL-2         | 5500     |           |            | 9v        | No  | Yes           |                        | ECOROW / ECOROR       |
| Minispot 200   | 200          |              | 12v 50W halogen bulb      | 5500     | T4A       | T1.6A      | 9v        | No  | Yes           |                        | (not user-changeable) |
| Ministudio 202 | 200          | 60           | 12v 100W halogen bulb     | 5500     | T4A       | T1.6A      | 9v        | No  | Yes           |                        |                       |
| Ministudio 252 | 250          | 52           | 300W halogen bulb (64516) | 5500     | T4A       | F2A & FF4A | 9v        | No  | Yes           | Stepless Power Control |                       |
| Ministudio 402 | 400          | 65           | 300W halogen bulb (64516) | 5500     | T6.3A     | F2A & FF4A | 9v        | No  | Yes           | Stepless Power Control |                       |
| Ministudio 606 | 600          | 45           | 150W                      | 5500     | T4A       | F2A        | 9v        | No  | Yes           |                        |                       |
| Ministudio 802 | 800          | 105          | 300W halogen bulb (64516) | 5500     | T6.3A     | F2A & FF4A | 9v        | No  | Yes           | Stepless Power Control |                       |
| Profilux 200   | 25 - 200     | 42           | 75W halogen PROHAL        | 5500     | T3.15A    | -          | 9v        | Yes | Yes           |                        | COMREW-4/COMROR-4     |
| Profilux 400   | 50 - 400     | 67           | 150W halogen LUHAL-2      | 5500     | T3.15A    | -          | 9v        | Yes | Yes           |                        | COMREW-4/COMROR-4     |
| Profilux 600   | 75 - 600     | 94           | 250W halogen LUHAL-3      | 5500     | T3.15A    | -          | 9v        | Yes | Yes           |                        | PROREW                |
| Vari 2         | 35 - 250     | 60           | LUHAL-1                   | 5500     |           |            | 9v        | Yes | Yes           |                        | ARROW/ARREW           |
| Vari 5         | 65 - 500     | 85           | LUHAL-3                   | 5500     |           |            | 9v        | Yes | Yes           |                        | ARROW/ARREW           |
| Varilux 1000   | 60 - 1000    | 123          | 250W halogen B15d base    | 5500     | T10A      | -          | 9v        | No  | Yes           |                        | RAREW                 |
| Varilux 1000/s | 60 - 1000    | 123          | 650W halogen GX 6.35 base | 5500     | T10A      | F4A        | 9v        | No  | Yes           |                        | RAREW                 |
| Varilux 1000/s | 60 - 1000    | 123          | 650W halogen GX 6.35 base | 5500     |           |            | 9v        | Yes | Yes           |                        | RAREW                 |
| Varilux 1500   | 100 - 1500   | 147          | 250W halogen B15d base    | 5500     | T10A      | -          | 9v        | No  | Yes           |                        | RAREW                 |

|                   |                 |                 |                                 |             |              |              |              |     |                   |                                                       |                    |
|-------------------|-----------------|-----------------|---------------------------------|-------------|--------------|--------------|--------------|-----|-------------------|-------------------------------------------------------|--------------------|
| Varilux<br>1500/s | 100 -<br>1500   | 147             | 650W halogen<br>GX 6.35 base    | 5500        | T10A         | F4A          | 9v           | No  | Yes               |                                                       | RAREW              |
| Model             | Power<br>Output | Guide<br>No (m) | Modelling bulb                  | Temp<br>(K) | Main<br>fuse | Lamp<br>fuse | Synch<br>(V) | Fan | Built-<br>in cell | Other_Spec                                            | Tube_Code          |
| Varilux 250       | 15 -<br>250     | 60              | 150W halogen<br>B15d base       | 5500        | T6.3A        | -            | 9v           | No  | Yes               |                                                       | STUROW             |
| Varilux 500       | 30 -<br>500     | 85              | 150W halogen<br>B15d base       | 5500        | T6.3A        | -            | 9v           | No  | Yes               |                                                       | STUROW             |
| Varilux<br>500/s  | 30 -<br>500     | 85              | 300 halogen GX<br>6.35 base     | 5500        |              |              | 9v           | Yes | Yes               |                                                       | STUROW             |
| Variolite<br>1000 | 60 -<br>1000    | 145             | 650W halogen<br>PF 813          | 5500        |              |              | 9v           | No  | Yes               |                                                       |                    |
| Variolite<br>1200 | 80 -<br>1200    | 142             | 650W OSRAM<br>64540             | 5500        | T10A         | F4A          | 9v           | No  | Yes               |                                                       |                    |
| Variolite<br>1800 | 110 -<br>1800   | 164             | 650W OSRAM<br>64540             | 5500        | T16A         | F4A          | 9v           | No  | Yes               |                                                       |                    |
| Variolite<br>2000 | 2000            | 200             | 650W halogen<br>PF 813          | 5500        |              |              | 9v           | No  | Yes               |                                                       |                    |
| Variolite<br>300  | 20 -300         | 72              | 300W OSRAM<br>64516             | 5500        | T6.3A        | F2A          | 9v           | No  | Yes               |                                                       |                    |
| Variolite<br>600  | 40 -<br>600     | 100             | 650W OSRAM<br>64540             | 5500        | T10A         | F4A          | 9v           | No  | Yes               |                                                       |                    |
| Variolite<br>900  | 50 -<br>900     | 120             | 650W OSRAM<br>64540             | 5500        | T10A         | F4A          | 9v           | No  | Yes               |                                                       |                    |
| Varispot<br>500   | 30 -<br>500     | 78              | 12v 50W<br>halogen<br>LUSJOD    | 5500        |              |              | 9v           | Yes | Yes               | Guide No (m).28 with<br>Spot attachment (+500<br>PRO) | LUSROR             |
| Xenolux<br>1000   | 60 -<br>1000    | 123             | 230v 650W<br>halogen<br>VAJOG-2 | 5500        | 10A          | -            | 12v          | Yes | Yes               | Socket for computer<br>control                        | RAREW /<br>RARER   |
| Xenolux<br>1500   | 100 -<br>1500   | 147             | 230v 650W<br>halogen<br>VAJOG-2 | 5500        | 10A          | -            | 12v          | Yes | Yes               | Socket for computer<br>control                        | RAREW /<br>RARER   |
| Xenolux<br>250    | 15 -<br>250     | 60              | 230v 250W<br>halogen<br>LUHAL-3 | 5500        | 6.3A         | -            | 12v          | Yes | Yes               | Socket for computer<br>control                        | STUROW /<br>STURER |



|                |             |    |                                 |      |      |   |     |     |     |                                |                    |
|----------------|-------------|----|---------------------------------|------|------|---|-----|-----|-----|--------------------------------|--------------------|
| Xenolux<br>500 | 30 -<br>500 | 85 | 230v 250W<br>halogen<br>LUHAL-3 | 5500 | 6.3A | - | 12v | Yes | Yes | Socket for computer<br>control | STUROW /<br>STURER |
|----------------|-------------|----|---------------------------------|------|------|---|-----|-----|-----|--------------------------------|--------------------|

## PORTAFLASH STUDIO FLASH EQUIPMENT

| Model | Power Output | Guide No (m) | Modelling bulb            | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec                                | Tube_Code                        |
|-------|--------------|--------------|---------------------------|----------|-----------|-----------|-----------|-----|---------------|-------------------------------------------|----------------------------------|
| 336VM | 100          | 36           | 240v 60W mini E.S fitting | 5600     | F2A       | -         | 8v        | No  | Yes           | Power selection stepped (1/4, 1/2 & Full) | (not user-changeable)            |
| 536   | 160          | 36           | 240v E.S fitting          | 5600     | F3A       | F2A       | 8v        | No  | Yes           | Power selection stepped (1/4, 1/2 & Full) | Unknown (Available from Jessops) |
| 550   | 320          | 50           | 240v E.S fitting          | 5600     | F4A       | F2A       | 8v        | No  | Yes           | Power selection stepless (1/4 to Full)    | Unknown (Available from Jessops) |

## POWERFLASH STUDIO FLASH EQUIPMENT

| Model | Power Output | Guide No (m) | Modelling bulb            | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec      | Tube_Code             |
|-------|--------------|--------------|---------------------------|----------|-----------|-----------|-----------|-----|---------------|-----------------|-----------------------|
| AM200 | 200          | 30           | 150W halogen GX 6.35 base | 5500     |           |           |           | No  | No            |                 | (not user-changeable) |
| MD400 | 400          | 45           | 150W halogen GX 6.35 base | 5500     |           |           |           | No  | No            |                 | (not user-changeable) |
| MD800 | 800          | 82           | 300W halogen GX 6.35 base | 5500     |           |           |           | Yes | No            | Strobe function | (not user-changeable) |
| PR200 | 200          | 30           | 150W halogen GX 6.35 base | 5500     |           |           |           | No  | No            |                 | (not user-changeable) |

|       |     |    |                              |      |  |  |  |    |    |  |                           |
|-------|-----|----|------------------------------|------|--|--|--|----|----|--|---------------------------|
| PR400 | 400 | 45 | 150W halogen GX<br>6.35 base | 5500 |  |  |  | No | No |  | (not user-<br>changeable) |
|-------|-----|----|------------------------------|------|--|--|--|----|----|--|---------------------------|

---

## PROLINCA STUDIO FLASH EQUIPMENT

| Model | Power Output | Guide No (m) | Modelling bulb        | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec                 | Tube_Code                 |
|-------|--------------|--------------|-----------------------|----------|-----------|-----------|-----------|-----|---------------|----------------------------|---------------------------|
| 125   | 125          | 34           | 240v 100W E.S fitting | 5500     |           |           |           | No  | No            |                            | (not user-<br>changeable) |
| 250   | 250          | 49           | 240v 250W E.S fitting | 5500     |           |           |           | No  | No            |                            | (not user-<br>changeable) |
| 400   | 400          | 63           | 240v 250W E.S fitting | 5500     | T2.5A     | -         |           | No  | Yes           | Full or Half power setting | (not user-<br>changeable) |

---

## SYSTEMS IMAGING STUDIO FLASH EQUIPMENT

| Model | Power Output | Guide No (m) | Modelling bulb | Temp (K) | Main fuse | Lamp fuse | Synch (V) | Fan | Built-in cell | Other_Spec | Tube_Code                 |
|-------|--------------|--------------|----------------|----------|-----------|-----------|-----------|-----|---------------|------------|---------------------------|
| 1200G | 1200         |              | halagen        | 5500     | T10A      | F2A       | 12v       | No  | Yes           |            | (not user-<br>changeable) |
| 1500G | 1500         |              | halagen        | 5500     | T10A      | F2A       | 12v       | No  | Yes           |            | (not user-<br>changeable) |
| 1800G | 1800         |              | halagen        | 5500     | T10A      | F2A       | 12v       | No  | Yes           |            | (not user-<br>changeable) |
| 300E  | 300          |              | halagen        | 5500     | F5A       | F1A       | 12v       | No  | Yes           |            | (not user-<br>changeable) |

|      |     |         |      |      |     |     |    |     |                                          |
|------|-----|---------|------|------|-----|-----|----|-----|------------------------------------------|
| 300F | 300 | halagen | 5500 | F5A  | F1A | 12v | No | Yes | changeable)<br>(not user-<br>changeable) |
| 600F | 600 | halagen | 5500 | F5A  | F1A | 12v | No | Yes | (not user-<br>changeable)                |
| 600G | 600 | halagen | 5500 | T10A | F2A | 12v | No | Yes | (not user-<br>changeable)                |
| 900G | 900 | halagen | 5500 | T10A | F2A | 12v | No | Yes | (not user-<br>changeable)                |

